

# CAPNET DIGITAL USER GUIDE 2402

## FIXED FEATURE KEYS

**SPEAKER**- One way speaker-Listen only

**MESSAGES** -For retrieving messages-dials voice mail

**DROP**-Disconnects current call –used when conferencing

**REDIAL**-Redials last number dialed

**FEATURE**-For use to access features in guide

**MUTE**- For turning off handset microphone

**VOLUME CONTROL BUTTONS**-For adjusting speaker handset or ringer

**MESSAGE LAMP**-Lamp lights when voice mail message received and flashes to alert you to incoming calls

### PLACING A CALL

**Internal** - Hear dial tone  
Dial 5 digit extension number

**External** – Hear dial tone  
Dial \*99 and number within your own area code  
Long Distance – 9 and 1, area code and number for all calls outside your area code.

### HOLD

Press **HOLD** button

Retrieve Call:  
Press the call appearance button of the held call

### TRANSFER

Press **Transfer**  
Hear dial tone  
Dial extension or \*99 - plus number  
Announce call or wait for first ring  
Press **Transfer** button  
“Transfer Completed”

To Cancel and return to held call  
Press Call appearance button  
Reconnected to held call

### CONFERENCE

Join up to 6 Parties including yourself.  
Dial first party, announce conference  
Press **Conference**  
Hear dial tone  
Dial next party, when party answers  
Press **Conference**  
Repeat steps to add parties

To drop a 3<sup>rd</sup> party, busy or a no answer  
Press **Drop**  
You return to original party

### AUTOMATIC CALL BACK

Calls you back when line is busy or no answer.  
While listening to busy signal or a no answer  
Press **Feature**  
Press **Auto Call Back entry number (1-9 and 0 or \*or #)**  
Hear confirmation tone  
Hang up

When both parties are idle or free, you will be called  
Lift handset  
Call is placed

To Cancel:  
Press **Feature**  
Press **Auto Call Back entry number (1-9 and 0 or \*or #)**  
Hear confirmation tone-Hang up

### ABBREVIATED DIAL

Store numbers for one touch dialing  
Press **Feature**  
Press **Program Entry Number (1-9 and 0 or \*or #)**  
Or dial **\*83**  
Press **Feature**  
Press **Autodial Entry Number (1-9 and 0 or \*or #)**  
Dial number to be stored  
Press #, Hang up

To Make a Call After Programming:  
Hear dial tone  
Press **Feature**  
Press **Autodial Entry Number (1-9 and 0 or \*or #)**

### CALL PICKUP

To pick up another call  
Hear dial tone  
Press **Feature**  
Press **Call Pickup entry number (1-9 and 0 or \*or #)**  
Or dial **\*19**  
You are connected to caller

To Pick up a call while on a current call:  
Press **Switchhook**  
Press **Feature**  
Press **Call Pickup entry number (1-9 and 0 or \*or #)**  
Or dial **\*19**

To alternate between calls:  
Press **Switchhook once** connected to original caller

### CALL FORWARD BUSY DON'T ANSWER

Redirects calls to another extension on a busy or a no answer.  
Hear dial tone  
Press **Feature**  
Press **Call Forward Busy/Don't Ans Entry Number (1-9 and 0 or \* or #) (or \*05)**  
Hear second dial tone  
Dial extension number  
Hear confirmation tone, hang up

To Cancel:  
Hear dial tone  
Press **Feature**  
Press **Call Forward Busy/Don't Ans Entry Number (1-9 and 0 or \* or #) (or \*20)**

### CALL FORWARD FOLLOW ME

Redirects calls to another extension  
Hear dial tone  
Press **Feature**  
Press **Call Forward Entry Number (1-9 and 0 or \* or #) (or \*06)**  
Hear second dial tone  
Dial extension number  
Hear confirmation tone, hang up

To Cancel:  
Hear dial tone  
Press **Feature**  
Press **Call Forward Entry Number (1-9 and 0 or \* or #) (or \*20)**  
Hear confirmation tone, hang up

### SPEED CALLING PERSONAL LIST

Allows faster dialing of extension or outside numbers  
**To Program Personal List:**  
Hear dial tone, Press **Program (or \*83)**  
Hear dial tone, Press **1**, (for list number 1)  
Press Speed Code  
Lists of 10 use 1 thru 9 and 0 (0=10)  
Lists of 10 or more require 2 digits (1 thru 9 = 01 thru 09)  
Dial number to be stored (up to 24 digits)  
Press #, Hear confirmation tone  
**To Make a Call:**  
Hear dial tone, Press **\*81 and Speed Code**

**SPEED CALLING  
GROUP LIST**

**To Program a Group List:**

(A control station programs for a group of users including themselves. Obtain group list number from your agency representative.)

Hear dial tone, Press **\*84**

Hear dial tone, Enter a **4 digit group list number**

(ex. 20 becomes 0020.)

Press **2 digit Speed Code** (ex. 01, 02 etc.)

Dial number to be stored (up to 24 digits)

Press #, Hear confirmation tone.

**To Make a Call:**

Hear dial tone, Press **\*82 and Speed Code #**

**SEND ALL  
CALLS**

Sends calls to a predesignated number

Hear dial tone, Press **Feature**

Press **Send All Calls (1-9 and 0 or \*or #)** (or \*03)

To Cancel:

Hear dial tone, Press **Feature**

Press **Send All Calls (1-9 and 0 or \*or #)** (or \*86)

**QUESTIONS?**

Call Upstate Technical Assistance Center at extension 6-4000 Option 3 for additional user information. For repair call 6-4000 Option 1.

**PERSONALIZED SETTINGS**

**Ring Pattern.**

While on-hook, press Conference button

*You will hear current ring*

Press Conference button to cycle through eight patterns.

To save a ring pattern, *do not press conference again.*

This ring will be saved

**Visual Ring:**

Press the Feature button

*The feature lamp turns on*

Press Message button

*The Feature lamp turns off*

Do one of the following:

To enable visual ring option,

*Press\**

To disable visual ring

*Press #*

*Hear confirmation tone*