

# CAPNET/ 2500C

## SINGLE LINE TELEPHONE

### QUICK REFERENCE GUIDE

#### PLACING A CALL

**Internal** – Hear Dial tone  
Dial 5 digit extension number

**External** – Hear Dial tone  
Local - Dial \*99 and number  
Long distance - \*99 and 1, area code and  
Number for all calls outside your area  
Code

### FIXED FEATURES

**MUTE** **Pressing and holding** the button down blocks your conversation from being heard by the other party.

**FLASH** The flash feature simplifies access to system features that requires a momentary press of the switchhook. A press of the button provides a precisely timed switchhook “flash” regardless of how long the button is pressed.

**REDIAL** The telephone retains in memory the last number dialed (up to 28 digits) for a period of 24 hours, provided line power is maintained to the telephone.

**MESSAGE WAITING LIGHT** light goes on when a message is waiting at a central locations (voice mail).

#### HOLD

**Press R, Recall or Flash button**  
Or Press \*18

Retrieve call:  
Hit switchhook, phone rings, release switchhook  
Reconnected with caller

#### CALL PICKUP

Get dial tone, press \*19 or  
To pick up another call  
Press **R, Recall or Flash**, Hear dial tone  
Press \*19

To Disconnect and return to 1<sup>st</sup> caller  
Hit switchhook, phone rings, release switchhook  
Reconnected with 1<sup>st</sup> caller

#### TRANSFER

Press **R, Recall or Flash** button  
Hear recall dial tone  
Dial Extension number, announce call or  
Wait for first ring  
Hang up

If no answer  
Press **R, Recall or Flash** button **twice**  
Reconnected to held call

#### CONFERENCE CALL

Joins you and two (2) other parties  
Dial first party, announces Conference  
Press **R, Recall or Flash** button  
Hear recall dial tone  
Dial second party, when party answers  
Press **R, Recall or Flash** button  
All are joined.

If number is busy or does not answer:  
Press **R, Recall or Flash** button **twice**  
Rejoins to original party

#### CALL FORWARD FOLLOW ME

Redirects calls to another extension  
Hear dial tone, Dial \*06  
Hear dial tone, Dial extension number  
Hear confirmation tone, hang up

To Cancel:  
Hear dial tone, Dial \*20  
Hear confirmation tone, hang up

#### CALL FORWARD BUSY DON'T ANSWER

Redirects calls to another extension on a busy or a no answer.

Hear dial tone, Dial \*05  
Hear dial tone, Dial extension number  
Hear confirmation tone, hang up

To Cancel:  
Hear dial tone, Dial \*20  
Hear confirmation tone, hang up

#### AUTOMATIC CALLBACK

Calls you back when line is busy or no answer

Press **R, Recall or Flash**, Hear recall dial tone  
Press \*07, Hear confirmation tone  
Hang up

When both parties are on hook, you will be called

To Cancel:  
Hear dial tone, Dial \*17  
Hear confirmation tone, hang up

#### SPEED CALLING PERSONAL LIST

Allows faster dialing of extension or outside numbers

**To Program Personal List:**  
Hear dial tone, Press \*83  
Hear dial tone, Press 1, (for list number 1)  
Press Speed Code  
Lists of 10 use 1 thru 9 and 0 (0=10)  
Lists of 10 or more require 2 digits  
(1 thru 9 = 01 thru 09)  
Dial number to be stored (up to 24 digits)  
Press #, Hear confirmation tone

**To Make a Call:**  
Hear dial tone, Press \*81 and Speed Code #

#### SPEED CALLING GROUP LIST

**To Program a Group List:**  
(A control station programs for a group of users including themselves. Obtain group list number from your agency representative.)

Hear dial tone, Press \*84  
Hear dial tone, Enter a **4 digit group list number**  
(ex. 20 becomes 0020.)  
Press 2 digit Speed Code (ex. 01, 02 etc.)  
Dial number to be stored (up to 24 digits)  
Press #, Hear confirmation tone.

**To Make a Call:**  
Hear dial tone, Press \*82 and Speed Code #

### QUESTIONS?

Call Education and Training at extension 6-1445

OR

OGS Telecommunications Help Desk at 486-4000