

NYC/CAPNET SINGLE LINE TELEPHONE QUICK REFERENCE GUIDE

PLACING A CALL

Internal – Hear Dial tone
Dial 4 digit extension number

External – For all call outside the system
Hear Dial tone, Dial 9-1-Area Code and
Number.

HOLD

Press **R, Recall or Flash** button
Or Press ***18**

Retrieve call:
Hit switchhook, phone rings, release switchhook
Reconnected with caller

CALL PICKUP

To pick up another call
Press **R, Recall or Flash**, Hear dial tone
Press ***19**

To Disconnect and return to 1st caller
Hit switchhook, phone rings, release switchhook
Reconnected with 1st caller

TRANSFER

Press **R, Recall or Flash** button
Hear recall dial tone
Dial Extension number, announce call or
Wait for first ring
Hang up

If no answer
Press **R, Recall or Flash** button **twice**
Reconnected to held call

CONFERENCE CALL

Joins you and two (2) other parties
Dial first party, announces Conference
Press **R, Recall or Flash** button
Hear recall dial tone
Dial second party, when party answers
Press **R, Recall or Flash** button
All are joined.

If number is busy or does not answer:
Press **R, Recall or Flash** button **twice**
Rejoins to original party

LAST NUMBER DIALED

Allows user to automatically redial last number dialed.
Hear dial tone
Dial ***12**
Previous Number is dialed.

CALL FORWARD FOLLOW ME

Redirects calls to another extension

Hear dial tone, Dial ***06**
Hear dial tone, Dial extension number
Hear confirmation tone, hang up

To Cancel:

Hear dial tone, Dial ***20**
Hear confirmation tone, hang up

Redirects calls to another extension on a busy
or a no answer.

Hear dial tone, Dial ***05**
Hear dial tone, Dial extension number
Hear confirmation tone, hang up

To Cancel:

Hear dial tone, Dial ***20**
Hear confirmation tone, hang up

Calls you back when line is busy or no answer

Press **R, Recall or Flash**, Hear recall dial tone
Press ***07**, Hear confirmation tone
Hang up

When both parties are on hook, you will be called

To Cancel:

Hear dial tone, Dial ***17**
Hear confirmation tone, hang up

Allows faster dialing of extension or outside numbers

To Program Personal List:

Hear dial tone, Press ***83**
Hear dial tone, Press **1**, (for list number 1)
Press Speed Code
Lists of 10 use 1 thru 9 and 0 (0=10)
Lists of 10 or more require 2 digits
(1 thru 9 = 01 thru 09)
Dial number to be stored (up to 24 digits)
Press #, Hear confirmation tone

To Make a Call:

Hear dial tone, Press ***81 and Speed Code #**

To Program a Group List:

(A control station programs for a group of users
including themselves. Obtain group list number from
your agency representative.)
Hear dial tone, Press ***84**
Hear dial tone, Enter a **4 digit group list number**
(ex. 20 becomes 0020.)
Press 2 digit Speed Code (ex. 01, 02 etc.)
Dial number to be stored (up to 24 digits)
Press #, Hear confirmation tone.

To Make a Call:

Hear dial tone, Press ***82 and Speed Code #**

QUESTIONS?

CIO/OFT Upstate Technical Assistance Center-1-888-784-
4647-Option 3 or for Repair 1-888-784-4647-Option 1