

# CALL PILOT VOICE MAIL QUICK REFERENCE GUIDE ROCHESTER OFT Help Desk 1-888-784-4647

## INITIALIZING YOUR VOICE MAIL

### LOG IN

Dial **8570** or Press **MESSAGE** key and  
From your desk – Press # **sign or**  
From another desk – **YOUR extension and # sign or**  
Outside the building – Dial **238-8570**  
**Extension number and # sign**

### ESTABLISHING NEW PASSWORD

Your Starter Password is "0" +Your Extension and # sign  
Password can be 4 – 16 digits long  
**Cannot be** your extension  
Press **84**  
Enter **Old** password and # **sign**  
Enter **New** Password again and # **sign**  
Enter **New** Password and # **sign**

### RECORD YOUR NAME

Press **82** then Press **9**  
Press **5**, wait for tone  
Record name, press # **sign**  
Press **2** to listen to name  
Press **76** to delete and re-record

## FUTURE LOGINS

### LOG IN

Dial **8570** or Press **MESSAGE** key and  
From your desk – Press # **sign**  
From another desk – **YOUR extension and # sign**

Outside the building – Dial **238-8570**

Your extension number and # sign  
Your password and # sign

## PLAYING YOUR MESSAGES

Log on to Mail Box  
Listen to Envelope  
Press **2** to listen to message

## END OF MESSAGE OPTIONS

**76** – Delete (76 is also used to undelete during current session)  
**72** – To Play Envelope  
    **6** – Next Message  
    **4** – Previous Message  
**86** – Enter message number and # sign for specific Message  
    **9** – Call Sender  
**71** – Reply to Sender  
**73** – Forwarding a Message

## PLAY BACK CONTROLS

**1** – Skip Back  
**3** – Skip Forward  
# - To Pause and  
**2** – To Continue  
**72**- To Play Envelope  
**21**- To Play Message Slower  
**23**- To Play Message Faster

## CREATING YOUR PERSONAL GREETING

Log into your Mailbox  
Press **82** and enter one of the following:

- 1** – For **External Greeting**
- 2** – For **Internal Greeting**
- 3** – For **Temporary Greeting**
- 9** – For **Personal Verification**

Press -  
**5** – begin recording  
**2** – to playback  
**76** – to delete or  
# - to approve  
**4** – to exit

### Temporary Greeting

#### To set Expiring Date and Time:

Press **9** – enter Month (2 Digits) and #, Date (2 Digits) and #, Time (Military) and #

#### If you wish the greeting to expire sometime today:

Press #, #, and expiry time today and #,

#### If you wish no expiry date:

Press #, #, #  
Press **4** – to exit

## COMPOSING A MESSAGE

Log into your Mailbox  
Press **75**  
Enter extension number(s) and # between each extension  
Press # and Press:  
**5** – to record      **79**-to send  
**2** – to playback      **76**-to play back

## EXPRESS MESSAGING

Sends a message to another mailbox without logging in  
Dial **8580** or **238-8580** (outside the system)  
Enter extension number and # sign  
Say your message at tone  
Hang up

## TAGGING OPTIONS

After recording a message the user can tag the message

By pressing:

- 1** – Urgent
- 4** – Private
- 5** – Acknowledge
- 6** - Timed Delivery
- 79** – To Send

## DISTRIBUTION LIST

### To Create List:

Log into Mailbox  
Press **85**  
Enter list number (1 to 9) and # sign  
Press **5**  
Enter Mailbox number, Press # after each Mailbox number  
Press # sign when finished

### To Delete List:

Log into Mailbox  
Press **85**  
Enter List number (1 – 9) and # sign  
Press **76** to delete (after hearing list number)

## TO CHANGE DIAL O (CUSTOM OPERATOR)

### Log into your mailbox

Press **80** for mailbox options  
Press **1** to change options  
Enter the new custom operator's number  
Press #